


*Breakout Multipin H16 in/out to 6x
Power Pro True*

EAN: 8717748622648



The Showgear PowerCore 2m.6p is a breakout power box with two Multipin H16 connectors (male/female) and 6 high-quality Power Pro True outlets from Seetronic. Its loop-through design connects all 8 channels from input to output, while channels 1-6 power the Power Pro True outlets. Each outlet includes a voltage indication LED for quick and convenient status checks. It is designed for seamless integration with the Showgear PowerCore series and is compatible with all PowerCore units equipped with a Multipin H16 output connector. It is also compatible with Harting HAN16 and other power distributor brands that use the 1-9 standard (pin 1+9 is channel 1, pin 2+10 is channel 2, etc.)

For flexible installation, the PowerCore 2m.6p offers multiple mounting holes for permanent setups and a quick-lock mounting point for fast, tool-free attachment using the optional PowerCore Quick Lock Bracket.

Special features:

- 2 Multipin H16 channels (1 in, 1 out) with loop-through functionality
- 6 Power Pro True outlets from Seetronic
- Voltage indication LED on each output
- Compatible with Multipin H16 and Harting HAN16
- Quick-lock mounting option for easy installation

Specifications:

Electrical Specifications and Connections

Power Supply	230 V AC 50/60 Hz
Rated Current (A)	16 A
Power Connector In	Multipin H16
Power Connector Out	Multipin H16 / Power Pro True

Mechanical Specifications

Length (mm)	310 mm
Height (mm)	102 mm
Width (mm)	150 mm
Weight	2.4 kg
IP Rating	IP20 (indoor use only)
Material	Metal
Colour	Black

Product Properties

LED Indicators	Power
----------------	-------

Thermal Specifications

Maximum Ambient Temperature	40°C
Minimum Ambient Temperature	-5°C

Rigging

Mounting Options	Quick-Lock / Wall
Fixed Mounting Option	11 mm
Safety Attachment	Yes